

# OSD-AMP120 2-Channel Power Amplifier

## Product Description:

The OSD-AMP120 2-channel power amp can be used as a remote amplifier, single zone amp, or rear channel amp for surround sound systems.

## Features:

Rated at 50 watts RMS per channel at 8 ohms, the OSD-AMP120 is big on features but low on price. A great fit as a single-zone, rear channel amp, or to bump up the power of your OSD Rock speakers, the AMP-120 includes two stereo inputs with automatic priority override, A, B, or A+B speaker selector switches and one auxiliary output.

- Complete custom installer feature set
- Front-panel mounted volume and balance knobs
- Manual or signal-sensing power-on
- 5-way speaker wire binding posts for bare wire or banana plugs
- 2-year warranty

## The Specs

- 50 watts RMS per channel into 8 ohm loads with .02% THD+N
- 60 watts RMS per channel into 4 ohm loads with .02% THD+N
- Maximum 8 ohm stereo output power at 1% THD+N: 60W
- Maximum 4 ohm stereo output power at 1% THD+N: 75W
- Maximum 8 ohm Bridged-Mono output at 1% THD+N: 160W
- Input needed to reach full output: 1.4v
- Frequency Response:  
(20Hz-20kHz)+1dB, -0.5dB;  
(5Hz-65kHz)+/-3dB
- Signal to Noise Ratio:  
107dB (A-Weighted)
- Dimensions: 2.9"H x 16.5"W x 9.25"D
- Power Consumption 500 Watts  
(all channels driven)
- Weight: 9.6 lbs



Find the OSD-AMP-120 at Outdoor Speaker Depot,  
[www.outdoorspeakerdepot.com](http://www.outdoorspeakerdepot.com)  
or call 888 779-4968.