

SPECIFICATION SHEET

Туре:	
Model:	
Project:	

MODEL LCS Landscape Series • Lighting Control System

CONTROLLER SPECIFICATIONS:

EXTERIOR CONSTRUCTION:

20-gauge polished, top-grade domestic, 304 stainless steel. Waterproof NEMA 3 stainless-steel housing for wall or pedestal mount

FINISH

Polished stainless steel with Smudge-Free clear powder-coat. Also available in Durable powder coat finish available in Black, Architectural Bronze, Dark Bronze, Granite, White, Architectural Brick, Light Bronze, Special Bronze, Glossy Gray, Rust, Hunter Green, Weathered Bronze, Weathered Iron, Graphite Metallic, Verde, Pewter, Mocha and Olde Finish. Custom Powder coat finishes available on request.

CONTROLLER CHARACTERISTICS:

Desgined to control 150 watts of lighting in three individual circuits/zones Controls and dims most LED light source with any mobile device from anywhere. Easily Accessible ON/OFF/APP rocker control switch. External antenna allows for connecting to WiFi at greater distances Can be used with most all low voltage power systems available today as well as retrofitted to most existing low voltage outdoor lighting system.


TERMINALS:


Oversized input terminals; common/12-15V input (from host transformer) **WIRING:**


LCS does not require 120V input. Receives power from host transformer.

All Vista Controllers are MADE IN THE U.S.A.

DIMENSIONS:







Vista Professional Outdoor Lighting reserves the right to modify the design and/or construction of the fixture shown without further notification.



SPECIFICATION SHEET

MODEL LCS Landscape Series • Lighting Control System

CONTROLLER ORDERING INFORMATION

TO ORDER LCS: Select appropriate choice from each column as in the following example.

EXAMPLE: LCS-150-B

SERIES	MODEL	FINISH
LCS	150-150 watt, three circuit	Smudge-free clear powder-coat
		Standard
		B - Black
		Z - Architectural Bronze
		DZ - Dark Bronze
		GT - Granite
		W - White
		Premium
		BR - Architectural Brick
		LZ - Light Bronze
		SB - Special Bronze
		GG - Glossy Gray
		R - Rust
		HG - Hunter Green
		WB - Weathered Bronze
		WI - Weathered Iron
		GM - Graphite Metallic
		Hand Finished
		G - Verde
		P - Pewter
		M - Mocha
		OF - Olde Finish

Note: When a finish is not specified, LCS Lighting Control System will be shipped with a clear, powder-coat finish.

FEATURES:

- Designed to control 150 watts of lighting in three individual circuits/zones.
- Controls and dims most LED light sources with any mobile device from anywhere.
- LCS does not require 120V input! Receives power from host transformer.
- Oversized input terminals; common/12-15V input (from host transformer).
- Waterproof NEMA 3 stainless-steel housing for wall or pedestal mount.
- · Vista's own 'cable-raceway' feature with drop-down tray for full and easy access to wiring compartment.
- Easily Accessible ON/OFF/APP rocker control switch.
- Contains LED indicator lights for 'power ON' and for each ZONE 1,2,3.
- Zone indicator LED's mimic specific zone brightness intensities.
- External antenna allows for connecting to WiFi at greater distances.
- Free App Store/Google Store availability. One account can control multiple units.
- Fine-Tune-Dimming gives the user an almost infinite ability to adjust and match output throughout enitre system.
- Can be used with most all low voltage power systems on the market today as well as retrofitted to most any existing low voltage outdoor lighting system.